



INDUCTANCE & RESISTANCE MEASUREMENT OF VYBRONICS PART #VZ6DH2B1501851

Test Date: 10-05-2022

Test Conditions: 20 +/- 2 C Humidity: 63 ~ 67 % RH

Test Equipment: Smart Tweezers LCR Meter, Model: ST5S, Calibration Date: 12-06-2021
Fluke True RMS Multimeter, Model: 117, Calibration Date: 02-07-2022

| Sample # | Inductance (uH) | Resistance (ohms) |
|----------|-------------------|---------------------|
| 1 | 172.3 | 28.8 |
| 2 | 173.6 | 28.7 |
| 3 | 169.2 | 28.9 |
| 4 | 169.0 | 28.9 |
| 5 | 165.9 | 28.6 |
| 6 | 169.0 | 28.3 |
| 7 | 177.7 | 29.0 |
| 8 | 175.5 | 28.5 |
| 9 | 184.0 | 28.9 |
| 10 | 175.4 | 28.9 |
| 11 | 172.2 | 28.5 |
| 12 | 167.7 | 28.2 |
| 13 | 169.2 | 28.2 |
| 14 | 170.4 | 28.4 |
| 15 | 165.5 | 28.5 |
| 16 | 166.6 | 28.8 |
| 17 | 178.0 | 28.8 |
| 18 | 168.7 | 28.5 |
| 19 | 170.1 | 29.0 |
| 20 | 177.7 | 28.4 |

| | | |
|------------|---------|-------|
| High Value | 184.0 | 29.0 |
| Low Value | 165.5 | 28.2 |
| Range | 18.5 | 0.8 |
| Average | 171.885 | 28.64 |

Tested BY:

A handwritten signature in black ink, appearing to read "Chares Tepper". The signature is written in a cursive style with a large initial "C" and a long, sweeping flourish at the end.

Chares Tepper
Sales Engineer